

## IT-8900

IT8912-600-480	600V	480A	12kW	1mV 1mA	$\pm(0.025\%+0.1\%FS)$ $\pm(0.05\%+0.1\%FS)$	15U
IT8912-1200-240	1200V	240A	12kW	10mV 1mA	$\pm(0.025\%+0.025\%FS)$ $\pm(0.05\%+0.1\%FS)$	15U
IT8915-150-960	150V	960A	15kW	1mV 1mA	$\pm(0.025\%+0.025\%FS)$ $\pm(0.1\%+0.1\%FS)$	15U
IT8918-600-720	600V	720A	18kW	1mV 1mA	$\pm(0.025\%+0.025\%FS)$ $\pm(0.1\%+0.1\%FS)$	24U
IT8918-1200-360	1200V	360A	18kW	10mV 1mA	$\pm(0.025\%+0.025\%FS)$ $\pm(0.05\%+0.1\%FS)$	24U
IT8922-150-1440	150V	1440A	22.5kW	1mV 10mA	$\pm(0.025\%+0.025\%FS)$ $\pm(0.1\%+0.1\%FS)$	24U
IT8924-600-960	600V	960A	24kW	1mV 1mA	$\pm(0.025\%+0.025\%FS)$ $\pm(0.1\%+0.1\%FS)$	24U
IT8924-1200-480	1200V	480A	24kW	10mV 1mA	$\pm(0.025\%+0.025\%FS)$ $\pm(0.05\%+0.1\%FS)$	24U
IT8930-150-1920	150V	1920A	30kW	1mV 10mA	$\pm(0.025\%+0.025\%FS)$ $\pm(0.1\%+0.1\%FS)$	24U
IT8930-600-1200	600V	1200A	30kW	1mV 10mA	$\pm(0.025\%+0.025\%FS)$ $\pm(0.1\%+0.1\%FS)$	37U
IT8930-1200-600	1200V	600A	30kW	10mV 1mA	$\pm(0.025\%+0.025\%FS)$ $\pm(0.1\%+0.1\%FS)$	37U
IT8936-600-1440	600V	1440A	36kW	1mV 10mA	$\pm(0.025\%+0.025\%FS)$ $\pm(0.1\%+0.1\%FS)$	37U
IT8936-1200-720	1200V	720A	36kW	10mV 1mA	$\pm(0.025\%+0.025\%FS)$ $\pm(0.05\%+0.1\%FS)$	37U
IT8945-150-2500	150V	2500A	45kW	1mV 10mA	$\pm(0.025\%+0.025\%FS)$ $\pm(0.1\%+0.1\%FS)$	37U

\*This information is subject to change without notice.