

# TM-81 Digital Multimeter



CAT IV 600V  
 LCD display with maximum reading of 1999  
 AC voltage range: 0 to 600V.  
 DC voltage range: 0 to 600V.  
 Auto power off (15 minutes).  
 ACV, DCV, Resistance, Diode, Continuity,  
 Capacitance, Range Hold, Data Hold, Max.  
 Accessories.

<b>Overvoltage Category</b>	CAT IV 600V, CAT III 1000V
<b>LCD Display</b>	1999 counts
<b>Sampling Rate</b>	2.5 times/second
<b>Auto Power Off</b>	Yes
<b>DC Voltage</b>	0.1mV to 600V $\pm(0.8\%$ of rdg + 1 dgts)
<b>AC Voltage</b>	0.001V to 600V $\pm(1.5\%$ of rdg + 3 dgt)
<b>Resistance/Accuracy</b>	200 $\Omega$ , 2k $\Omega$ , 20k $\Omega$ , 200k $\Omega$ , 2M $\Omega$ , 20M $\Omega$ ; $\pm(1.0\%$ of rdg + 3 dgt)
<b>Protection</b>	600Vrms
<b>Continuity Buzzer</b>	Yes
<b>Diode Test</b>	Test voltage 1.5 volts
<b>Range Hold</b>	Yes
<b>Data Hold</b>	Yes
<b>Max</b>	Yes
<b>Accessories</b>	Carrying case, Test Leads, Operating Manual, Battery

