

## YF-8050 AC Clamp Meter



CAT III 1000V  
3-3/4 digit LCD display with maximum reading of 4000.  
Overload indication.  
Low battery indication.  
AC voltage range: 0 to 750V.  
AC current range: 0 to 1000A.  
Peak Hold.  
Test Ranges: ACV, ACA, Resistance, Frequency, Continuity.  
Non-contact frequency measurement.  
Auto Power Off.  
Double Injection outer case.

<b>Maximum Current</b>	1000 Amps
<b>Display</b>	4000 counts
<b>Max. Conductor Size</b>	52mm
<b>AC Current</b>	1mA to 1000A, $\pm(1.5\%$ of rdg + 4 dgts)
<b>AC Voltage</b>	0.1V to 750V, $\pm(1.0\%$ of rdg + 4 dgts)
<b>Resistance</b>	0.1 $\Omega$ to 4000 $\Omega$ , $\pm(1.0\%$ of rdg + 2 dgts)
<b>Continuity Buzzer</b>	Yes
<b>Frequency</b>	1Hz to 4000KHz, $\pm(0.8\%$ of rdg + 3 dgts)
<b>Auto Power Off</b>	Yes
<b>Peak Hold</b>	Yes
<b>Dimensions</b>	250mm (L) x 70mm (W) x 35mm (D)
<b>Weight</b>	420g